Console Messages ESY0512I - ESY0599I

Message	Explanation	Action
ESY0512E - Unable to locate common area. XCOMJESC initialization failed.	The Common JES Interface could not locate Entire System Server's common area.	Contact Software AG technical support.
ESY0515I - Initialization sequence error for XCOMJESC.	A repeated initialization request was issued to the Common JES Interface.	Contact Software AG technical support.
ESY0519I - Subsystem .... is not supported by XCOMJESC.	Entire System Server is running under a subsystem that is neither JES2 nor JES3. The Common JES Interface can not access spool data.	Start Entire System Server under a supported subsystem (JES2 or JES3).
ESY0520I - SSI request .. failed with RC .. and SSOBRETN ..	A subsystem interface (SSI) request failed.	Contact Software AG technical support.
ESY0523E - Unable to determine nodename. XCOMJESC initialization failed.	The Common JES Interface could not determine the JES node name.	Contact Software AG technical support.
ESY0554I - Job Entry Subsystem is ...., nodename	The Common JES Interface has successfully initialized.	Verify the JES common name, version and node name to make sure Entire System Server is running under the correct subsystem.
ESY0556W - Support for .... is not implemented.	The Common JES Interface does not support the current version of JES2 or JES3.	Contact Software AG technical support to obtain a fix adding support for the current version of JES2 or JES3.
ESY0563I - $CBIO failed, RC .., MTTR ...., for	A request failed to read a control block from JES2 spool for the specified job id / job name.	Contact Software AG technical support.
ESY0567I - IATXBKIO failed, RC .., SPADR ...., for .... of	A request failed to read a control block from JES3 spool for the specified job id / job name.	Contact Software AG technical support.
ESY0571I - SSI request 71 failed, RC .., SSOBRETN .., SSJIRETN ...	A request failed to the JES job information service.	Contact Software AG technical support.
ESY0578E - Unable to obtain common area. XCOMJESC initialization failed.	The common JES interface could not obtain storage for its common constant parameter area.	Contact Software AG technical support.
ESY0579I - SSI request 79 failed with RT .. and SSS2REAS ..	A request failed to the SYSOUT API interface.	Contact Software AG technical support.
ESY0580I - SSI request 80 failed with RT .. and STATREAS ..	A request failed to the Extended Status interface.	Contact Software AG technical support.
ESY0599I - Error (un)allocating SYSOUT dataset, RC .., reason ....DSN..	An error occurred during allocation or unallocation of a SYSOUT dataset.	Contact Software AG technical support.